

# LineBox

LINE Gateway with PSTN support

LineBox introduction YouTube [https://youtu.be/ RUxIfTnQx8](https://youtu.be/RUxIfTnQx8)  
YouTube caption is available.

## Main Features

1. After LineBox is connected to office's existing PBX, analog conference phones, or regular phones, employees just pick up desk phone for LINE calls. No need of headset and microphone for LINE calls. Leave employee's mobile phone for more calls and add extra LINE call lines for your office
2. Make or receive LINE calls through desk phones or regular phones without changing employee's telephone habits
3. With LineBox, employees out of office, company's customers or suppliers can have a free LINE call to office to save expensive international or mobile calls
4. Support LINE speed dial number and the speed dial list can be exported for backup and imported for use
5. LINE DOD - Support automatic assigned LINE friend callout when phone is off hook – Direct LINE call
6. LINE DID - Incoming LINE calls will be forwarded automatically to the assigned PBX extension number for customer support
7. Switch between LineBox's LINE and Landline mode by pressing phone pound key “#”
8. Auto-Detection and Auto-Swap for “LINE” and “PHONE” RJ11 ports:



Normal Wiring



Wrong Wiring but Functional

9. Switch between a landline call and a LINE call by pressing phone keys “\* 1” and hang up the current call by pressing phone key “\*”
10. Add an interrupt LINE call or an interrupt landline call into a LINE & landline conference by pressing phone keys “\* 2”
11. “Audio recovery” button resolves LINE call party's problem of hearing each other

12. Support FSK type I like Caller ID for LINE incoming calls and display “LINE 566” or “566” and calling time
13. LineBox under IM mode supports other softphones like Teams, Lync/Skype for business, Google voice/hangouts, WhatsApp, Facebook Messenger, Zoom, Skype, ...as an audio device (Speaker/Microphone function). When LineBox connects with office’s existing conference phone, the conference phone will become a dedicated LINE or other softphone conference phone
14. Support popular PBXs and cordless phone sets including DECT, 5.8GHz, 2.4GHz, 900 MHz or others
15. Support international busy tone to make PBX application achievable
16. Support 2 REN standard loads and 20, 25, 30 and 50Hz ring signal frequency
17. Support LineBox software online upgrade and latest software version check/download
18. LineBox can run recent the SkyBox S1 software to work as a Skype gateway

### ***Minimum System Requirement***

---

- One PC running at 1G Hz or better, 512 MB RAM and one spare USB port
- PC with Microsoft Windows 11, 10, 8, 7 and Windows LINE 9.1.2.3379 version

### ***Product Specification***

---

- USB 1.1 plug and play, USB bus power, No external power
- Two RJ-11 ports. One Phone (FXS) port is for standard analog or cordless phone sets (Or standard PBX analog trunk line); the other Line (FXO) port is for traditional landline
- L x W X H: 95 X 66 X 22 mm

### ***Product Application***

**LineBox** LINE PBX Application **Person in Office**



**Contact Information**

Regin Technology Corp. LTD.  
 Mr. Henry Chou  
 Office: 886-3-5735360  
 Mobile: 886-936071552  
 Email: henry@regintech.com.tw  
 Address: 3F, NO. 41, Lane 42, Dongguang Rd., Hsinchu, Taiwan  
 Web: <https://www.regintech.com.tw>  
 Skype: regin.skype  
 LINE: Henry Chou (Scan right-hand QR code or search phone 0936071552)

